Apparatus and Method for Noise Reduction

Field of the Invention

This invention relates to noise reduction and more particularly, to an apparatus and

5   method for reducing noise in cellular telephones.

Background of the Invention

In communications, noise is an undesirable element. Noise hampers accurate reception

of transmitted information. There are several sources that cause this noise. In a communication

10   system such as a GSM system as illustrated in Fig. 1, for example, TDMA noise results from a

discontinuous transmission of the radio frequency (RF) signal. The discontinuous nature of the

signal manifests itself as a pulsed transmission. The pulsed transmission causes a pulsed current

consumption in the power amplifier (PA) of a communication device. The pulsed current

consumption produces a magnetic field of sufficient magnitude to generate an audible sound in

15   some devices.

In general, a sound generator (such as a buzzer or ringer) in a cellular communication

device (such as a mobile phone) similar to buzzer 200 illustrated in Fig. 2, consists of an inductor

210 which, when current I is driven through, creates a magnetic field. The magnetic field moves

a magnetic material that impacts a plate-like element to generate an audible sound. The buzzer

20   or ringer is designed to generate a sound when AC current flows through. This sound from the

buzzer or ringer may be used to indicate an incoming call for example.

The sound level in buzzer 200 may be defined by:

$$Sound_{buzzer} = K_1 * I_{buzzer} \qquad (1)$$

1

where I_{buzzer} is the AC current driven through the inductor and the constant K_1 is

dependent on the buzzer construction. A good buzzer is designed to obtain a good sound level

pressure with a small current. Current consumption is reduced and design of the driving circuit

is made easier. A general rule is that an increased inductance value results in bigger K_2.

5   In order to drive the buzzer to result in a ring, the current through the inductor 210 cannot

be constant. If a non constant current loop is located near the buzzer, the resulting magnetic field

may be strong enough to move the magnetic material in the buzzer and therefore, to produce

acoustic noise. This noise, however, is undesirable and has to be eliminated or minimized in

order to prevent disruption to communication. The undesirable noise resulting from the non-

10   constant current may be represented by the following relationship:

$$Noise_{buzzer} = K_2 * I_{loop} \qquad (2)$$

where K_2 is dependent on the coupling between the buzzer and the printed circuit board

(PCB) and I_{loop} is the non-constant current in the loop as described above. This current (i.e., I_{loop})

is non constant due to the discontinuous transmission in the GSM system. The coupling depends

15   on a plurality of factors such as the area of the current loop that generates the noise, area of the

material that forms the inductor inside the buzzer, the distance between the current loop and the

buzzer and the relative position of the buzzer and the loop. A bigger loop area causes a stronger

magnetic field. The magnetic field attenuates rapidly as the buzzer is located farther from the

loop which causes the field. A bigger coupling may be achieved when the loop is, as usually the

20   case, perpendicular to the axe of the buzzer coil.

In order to minimize or eliminate $Noise_{buzzer}$, K_2 in equation (2) above has to be

minimized. Existing solutions are focused on minimizing the current loop area and preventing

the coupling between the buzzer and the PCB. In attempting to minimize the current loop area,

some noise reduction may result. The noise, however, cannot be eliminated as the current loop

area cannot be reduced to zero. This is due to connections for the battery, the power amplifier

and other components in the power supply loop. In order to prevent coupling between the

acoustic part, i.e., the buzzer, and the source of the current loop, i.e., the power amplifier, these

5   two elements have to be spaced apart. This is not easily accomplished as the spacing required

for separating the power amplifier and the acoustic parts is simply not available in cellular

phones which are constantly being made smaller.

What is desired, therefore, is a method and apparatus for overcoming the limitations

described above.

10

Summary Of The Invention

Accordingly, an object of the present invention is to provide an apparatus and a method

for minimizing noise.

Another object of the present invention is to provide an apparatus and a method for

15   eliminating or canceling noise.

A further object of the present invention is to provide an apparatus and method for

canceling noise.

These and other objects of the present invention are achieved by introducing a

cancellation acoustic output that is equal in magnitude to a generated noise.

20

Brief Description Of The Drawings

The above objects and features of the present invention will be more apparent from the following description of the preferred embodiments with reference to the accompanying drawings, wherein:

5   Figure 1 illustrates a general communication system;

Figure 2 illustrates a buzzer and equivalent circuit;

Figure 3 illustrates a portion of a circuit board layout for a communication device;

Figure 4 illustrates acoustic output from the buzzer of a communication device;

Figure 5 illustrates a portion of a circuit board layout for a communication device

10 according to exemplary embodiments of the present invention; and

Figure 6 illustrates acoustic output from the buzzer of a communication according to exemplary embodiments of the present invention.

Detailed Description

In the following description, for purposes of explanation and not limitation, specific details are set forth, such as particular circuits, circuit components, techniques, etc. in order to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that the present invention may be practiced in other embodiments that depart from these specific details. In other instances, detailed descriptions of well-known methods,

20 devices and circuits are omitted so as not to obscure the description of the present invention.

The noise represented by $Noise_{buzzer}$ (in equation 2) above may be eliminated by introducing an acoustic output (designated as "Cancellation_Signal") that is equal in magnitude but opposite to the $Noise_{buzzer}$. This may be represented by:

Cancellation_Signal = - K_2 * I_{loop} (3)

Both K_2 and I_{loop} are known. The value of K_2 is based on the buzzer selected and the

PCB layout that is implemented. I_{loop} may be determined from the power control circuitry of the

communication device.

5   The introduction of a cancellation noise may be accomplished by one of three methods.

In the first of these methods, the source of the noise, I_{loop}, may be measured and a

corresponding cancellation signal can be created. The cancellation signal may be created

utilizing analog circuitry, such as amplifiers and filters, that could be adjusted for the

characteristics of the specific design of the communication device, It may also be created by

10   utilizing analog to digital (A/D) converters, digital signal processing and digital to analog (D/A)

converters. While this approach may be more flexible and easily adjustable, it is more complex

to implement.

According to a second method, a noise reduction algorithm may be programmed into the

RF power management ASIC ("application specific integrated chip") which is used in

15   communication devices such as a phone. The ASIC can produce the cancellation signal since the

ASIC can determine the exact amount of current that is driven from the battery to the power

amplifier (i.e., I_{loop}). Although the redesign of the ASIC may involve a high initial cost, it can be

performed in a manner such that the main parameters of the cancellation algorithm may be

implemented through the use of software executing in the main controller of a communication

20   device thereby enabling a solution to be more easily adaptable to several (phone) designs.

A third method that is more economical is through the addition of analog circuitry to the

communication device. This is easier to implement as the ASIC need not be redesigned. In

order to obtain noise cancellation using analog circuitry, an existing property of the power

supply signal (V_{bat}) can be used.

A principal advantage of the third method is the price and ability to implement at a later

stage of development or manufacture. This method needs only a few spaces in the printed circuit

5   board (PCB) and no redesign of the existing components already on the PCB.

The power supply signal V_{bat}, illustrated in Figs. 3 and 5, should, in theory, be a constant

signal. However, since the battery is not an ideal voltage source due to non-zero internal

resistance, a voltage drop across the internal resistance is present when there is current

consumption in the power amplifiers (P.A.). A power amplifier converts DC power of the

10   battery to a radio frequency (RF) signal having adequate power to enable the communication

device to transmit a signal to a base station. The power requirements, specified or requested by

the base station, for facilitating communication between the base station and a mobile

communication device vary. Typically, in a GSM 900 class 4 terminal, between 3 milliwatts and

2 watts are needed and in a DCS 1800 or PCS 1900 class 1 terminal, between 1 milliwatt and 1

15   watt are needed. The efficiency of the PA decreases as the output power increases. Therefore,

the current consumption may vary depending on the power needed either by the communication

device to communicate with a base station or specified by the base station. This voltage drop

may be represented by:

$$V_{batdrop} = R_{int} * I \qquad\qquad (4)$$

20   where R_{int} is the internal resistance of the battery (or, power source) and is dependent on

the battery construction. I is the current taken from the battery to provide power to the device.

During transmission from the communication device, the main contribution to the power

consumption comes from the power amplifier and I is approximately equal to I_{loop} where I_{loop} is

the current that flows from the battery to the power amplifier and back to the battery thus

creating a current loop (as described earlier) in the PCB. Therefore,

$$V_{batdrop} = R_{int} * I_{loop} \qquad (5)$$

Fig. 3 illustrates a conventional buzzer driving circuit and Fig. 5 illustrates a buzzer

5   driving circuit according to exemplary embodiments of the present invention. Since V_{bat}

provides the needed power to the buzzer, a path between the battery and the buzzer may be

closed to allow an amount of current to flow through the buzzer. This current flow may be

obtained by adding a resistor such as R_{650} in Fig. 5, for example. In order to avoid dc current and

therefore, eliminate power consumption in the buzzer which does not produce noise but causes

10   power consumption, a capacitor such as C_{650}, for example, may be added in series with R_{650} as

shown in Fig. 5.

The internal resistance R_{buzzer} of the buzzer is much lower than R_{650}. Therefore, when

R_{650} is placed in series with R_{buzzer}, the additional resistance from R_{buzzer} is negligible relative to

R_{650}. Therefore, the current through the buzzer of Fig. 5 may be represented by:

15                        $$I_{buzzer} = V_{batdrop}/R_{650} \qquad (6)$$

Using equation (5) above, this may be rewritten as

$$I_{buzzer} = (I_{loop} * R_{int})/R_{650} \qquad (7)$$

Referring back to equation (1), the sound produced by this current is:

$$Sound_{buzzer} = (K_1 * I_{loop} * R_{int})/R_{650} \qquad (8)$$

20   With reference to equation (3), this level (i.e., $Sound_{buzzer}$) equals the noise needed to

cancel it. This relationship may be represented by:

$$(K_1 * I_{loop} * R_{int})/R_{650} = - K_2 * I_{loop} \qquad (9)$$

Therefore,

$$(K_1 * R_{int})/R_{650} = - K_2 \qquad (10)$$

The negative value for K_2 may be achieved by adjusting the manner in which the buzzer

is connected. If it is improperly connected, the noise is doubled. If, on the other hand, it is

properly connected, the noise is cancelled. The value of the parallel resistor R_{650} may be:

$$R_{650} = (R_{int} * K_1)/K_2 \qquad (11)$$

Since R_{int} is small (approximately 50mΩ) R_{650} must be quite high (approximately 1.2kΩ)

because $K_2 \ll K_1$ (the parasitic coupling is much lower than the coupling of the driving circuit).

K_2 cannot be calculated easily without a precise knowledge of the buzzer and the current

distribution across the PCB. The current distribution is hard to obtain due to return currents

through the ground plane and has to be recalculated each time the layout of the PCB is changed.

It is more practical to obtain the value of R_{650} by testing (in a laboratory, for example). A

variable resistor may be mounted and the noise can be measured for different resistance values

and the resistance value that results in minimizing the noise may be chosen.

Even though R_{int} varies between batteries, noise minimization may be achieved using

apparatus and method according to exemplary embodiments of the present invention. Noise

cancellation according to exemplary embodiments of the present invention is illustrated in Fig. 6.

Fig. 4 illustrates noise from the buzzer of a communication device with the circuit layout of Fig.

3. As seen in Fig. 6, the noise from the buzzer is effectively cancelled out by the circuit layout

of Fig. 5 which incorporates the additional resistor such as R_{650}.

As discussed above, a method of the present invention may also be implemented by an

algorithm which generates a cancellation noise. This is a more complex approach even though it

is more accurate. In the alternative, the above described approach highlights a simpler solution

to the problem of noise cancellation by using the power supply from the battery, V_{bat} by adding a resistor and a capacitor.

The foregoing has described the principles, preferred embodiments and modes of operation of the present invention. However, the invention should not be construed as being limited to the particular embodiments described above. For example, the present invention can be used in loudspeaker to reduce the noise by providing a location (i.e., space) for the aforementioned capacitor and a resistor in the PCB. The above-described embodiments should be regarded as illustrative rather than restrictive, and it should be appreciated that variations may be made in those embodiments by those skilled in the art without departing from the scope of the present invention as defined by the following claims.